

KMAX S 50 Standalone Access Control

We offer the smart and safe way to enter your home.



Specification

- The storage capacity of 2,000 user card and 2,000 user password.
- Open three ways: card, password, card and password.
- Ultra-low power consumption: standby current is less than 30 ma.
- Independent password
- User can change and modified password code them self.
- Swipe to open the door of time is less than 0.1s
- Card type: EM (ID Card) IC card is optional



Break Glass



Power Supply



Proximity Card



Kmax S 50



Key Switch



Push Button



PROGRAMMING CODE 编程代码	[####] [123456] [#], DEFAULT = 123456 (默认)
CHANGE PROGRAMMING CODE 更改编程代码	[0] [NEW 6-DIGITS] [#] [REPEAT 6-DIGITS] [#] 新 6 位数字 重复 6 位数字
ADD USER CARD BY CONTINUOUSLY 添加多个用户卡	[1] [SWIPE NEW CARD] [#], START FROM 0001~2000 刷新卡, 数字从 0001 开始至 2000
PROGRAM TIMER (IN SECOND) 设置时间 (秒)	[5] + [XX] + [#], SET IN : 01~99
SET NEW USER PASSWORD 设置新用户密码	[6] + [XXXX] + [#] + [REPEAT : XXXX] + [#], EXAMPLE : 1234 #
DELETE USER CARD ONE BY ONE 逐张删除用户卡	[30] + [SWIPE CARD] + [#]
DELETE USER CARD BY NUMBER 按编号删除用户卡	[31] + [0001 ~ 2000] + [#]
DELETE ALL USER CARDS 删除所有用户卡	[32] + [9999] + [#]
EXIT SYSTEM 退出设置	[#]
RESET FACTORY DEFAULT 恢复出厂默认设置	TURN-OFF POWER, SWIPE [ON] DIP-SWITCH AND TURN-ON POWER, KEEP 2 TIMES SHORT-BEEP & FLASHING GREEN, AFTER TURN OFF DIP-SWITCH. 关闭电源, 打开 DIP 的 [ON], 再打开电源, 电板会发出短促的响声并闪烁绿灯, 关闭 DIP.



TURN-OFF POWER, SWIPE [ON] DIP-SWITCH & TURN-ON POWER, KEEP 2-TIMES SHORT-BEEP & FLASHING GREEN, AFTER TURN OFF DIP-SWITCH.

